PROGRAM CHAINING ROUTINE — Block No. 0000C

	Card Columns and Read-In Locations	OP	A	B	d	Remarks
	001	,	008	012		Set Word Marks for Card #2.
	008	,	019			
	012	,	026	030		
	019	L	065	368		Relocate Program Chaining Routine into Locations 333-368.
	026	1	001			Read Card #3 and branch to Location 001.
Card #2 (Relocated Program Chaining Routine)						
	333	,	008	012		Set Word Marks.
	340	,	001			
	344	1	001			Read and branch to Location 001.
	**348	1				Read.
	349	B	361	080	A	If A in column 80, branch to Location 361 to begin loading next program.
	357	B	421			If no A in column 80, branch to same program.
	361	/	340	080		Clear Read Area and branch to Location 340 to set Word Mark in 001, Read, and begin loading next program. NOTE: Word Marks for relocated Program Chaining Routine set up by Card #3.
	001	,	037	044		Set Word Marks for Card No. 3.
	008	N	000			
Card #3	012	,	340	344		
	019	,	348	349		Set Word Marks for relocated Program
	026	,	357			Chaining Routine.
	030	,	361	368		
	037	/	333	080		Clear Read Area and branch to Program Chaining Routine.

** All test programs will branch to Location 348 to Read a card and test for the letter A in column 80.

When programs are transferred from cards to tape by the Write Test Tape Routine (Block No. 5300), the OP code 1 in Location 348 is changed to BS88. This instruction causes the Program Chaining Routine to branch to the Read Test Tape Routine (Block No. 5310) to read a tape record instead of a card.