

CUSTOMER ENGINEERING TESTS  
FOR THE 1401 DATA PROCESSING SYSTEM

Block No. 0230A

MOVE AND ZERO SUPPRESS

Purpose of Test

To test the Move and Zero Suppress circuitry by moving the A Field with high order zeros and punctuation symbols, and a sign in the units position, into the Result Is print area and comparing the results with the Result Should Be Field. For unequal conditions the machine either stops to permit console checking or prints the results depending upon the setting of Sense Switch E.

Units Required

1401 Processing Unit  
1402 Card Reader or 729 Tape Drive  
1403 Printer (optional)

<u>Operations Used</u>	<u>Code</u>
Clear	(/)
Set Word Mark	(,)
Load	(L)
Move and Zero Suppress	(Z)
Compare	(C)
Branch	(B)
Print	(2)
Stop (error)	(.)

Method of Test

The complete test block consists of the following cards:

1. Title Card (0A)
2. Two Program Chaining Routine Cards (02-03)
3. Three Title and Headings Print Routine Cards (04-06)
4. Four special program cards to set up instructions that are effective only when tests are run from tape (07-10)
5. Program Instruction Cards (11-46)
6. Detail Cards (47-64)

Four Sense Switches may be brought into play as follows:

- Sense Switch B ON - permits scoping of the Move and Zero Suppress operations as often as desired.
- Sense Switch C OFF - no printing for correct results.  
ON - prints for correct results.
- Sense Switch D ON - repeats the program for an individual card as often as desired.
- Sense Switch E OFF - prints for error results.  
ON - stops for error results.