

PROGRAM LISTING

PRINT WORD MARKS                      BLOCK 1010E

.008012,019,02603EL0653681001,008012,00110011E361080A8421/340080 1 OF 2 IC IC8 02  
.037044NGCO,340340,348349,357,361368/333080 PRGM. CHAIN. ROUTINE 2 OF 2 IC IC8 03  
L057S4510012,045L0772/72/2772#/40/60#/80L/892702/2702413            CARD 1 OF 3 IC IC8 04  
.019026,033,040044,051051/340001                      TITLE PRINT ROUTINE    CARD 2 OF 3 IC IC8 05  
.S01505,512,513517,518525,529536,537541,545/333080                      CARD 3 OF 3 IC IC8 06

LOAD	INST	ADDR	ADDR	OP	A	B	REMARKS	
396	377	F	359			5611	USE WHEN TESTS ARE RUN FROM TAPE	07
404	385	F	58E				**	08
408	389	M	000				**	09
412	393	M	360			392	**	10
419	400	Z	352				START TEST	11
423	404	Z						12
424	405	L	654			522	MODIFY TITLE PRINT TO SKIP HEADINGS	13
431	412	F	500			5621	BR TO TITLE PRINT ROUTINE IF 1 IN 552	14
439	420	.	200				SET WORD MARK IN 200	15
443	424	C	459			332	MOVE LOZENGE INTO 332	16
450	431	M	332			331	MOVE LOZENGE INTO ALL PRINT POSITIONS	17
457	438	M	660			472	MOVE 201234 IC START A & B OF INSTR 466	18
464	445	M	660			479	MOVE 267300 IC START A & E OF INSTR 473	19
471	452	Z					PRINT WORD MARKS	20
473	454	B	452			E	B ON TO SCOPE	21
478	459	F	467			474	CLEAR WORD MARKS IN 467 AND 474	22
485	466	.	201			234	SET TWO WORD MARKS IN PRINT AREA	23
492	473	.	267			300	SET TWO WORD MARKS IN PRINT AREA	24
499	480	C	479			669	COMPARE LAST POSITION SET WITH 333	25
506	487	F	490				UNEQUAL-BRANCH TO SET WM IN 467 AND 474	26
511	492	F	521				EQUAL-BRANCH TO BEGIN REMOVING WMS	27
515	496	.	467			474	SET WORD MARKS IN 467 AND 474	28
522	503	A	676			472	ADD 1001 IC INCREMENT AB OF INSTR 466	29
529	510	A	676			479	ADD 1001 IC INCREMENT AB OF INSTR 473	30
536	517	B	452				LOOP TO PRINT WORD MARKS	31
546	521	M	660			548	MOVE 201234 IC START A & B OF INSTR 542	32
547	528	M	660			555	MOVE 267300 IC START A & B OF INSTR 549	33
554	545	F	543			550	CLEAR WORD MARKS IN 543 AND 550	34
561	542	#	201			234	CLEAR TWO WORD MARKS IN PRINT AREA	35
568	549	#	267			300	CLEAR TWO WORD MARKS IN PRINT AREA	36
575	556	Z	562			#	PRINT UNCLEARED WORD MARKS & BRANCH	37
580	561	.					ERROR STOP IF NO BRANCH	38
581	562	B	556			#	B ON TO SCOPE	39
586	567	C	555			672	COMPARE LAST POSITION CLEARED WITH 332	40
593	574	F	586				UNEQUAL-BRANCH TO SET WM IN 543 AND 550	41
598	579	B	420			D	EQUAL-D CA TO REPEAT TEST	42
603	584	B	348				BRANCH TO READ NEXT RECORD	43
607	589	.	543			550	SET WORD MARKS IN 543 AND 550	44
614	595	A	676			548	ADD 1001 IC INCREMENT AB OF INSTR 542	45
621	602	A	676			555	ADD 1001 TO INCREMENT AB OF INSTR 549	46

1010B-4

DATE								
ENG. CHG. NO.								