

Procedure for Running Branch Channel 9 and 12 Test from Tape

1. Manually enter "1" in Location S61.
2. Set Sense Switch "F" to the OFF position.

NOTE: This will allow the Branch Channel 9 and 12 Test to be executed with all other tests that may be chained.

Procedure for Running ONLY Branch Channel 9 and 12 Test from Tape

1. Manually enter Block No. 2020 in Locations S73-S76, and "1" in Location S61.
2. Set Sense Switch "F" to the ON position.

NOTE: This will allow only the Branch Channel 9 and 12 Test to be executed, by-passing all the others.

Checking Procedure

Two print-out examples are shown below which can be used to visually check the results.

EXAMPLE OF CORRECT PRINT-OUT:

BRANCH CHANNEL 9 & 12    2020B

(Spacing may vary from 2 to 40 spaces depending upon the position of the carriage tape when the title is printed) →

<u>Line No. on Tape</u>	(blanks)	
1 or 41		
2 or 42	DID NOT BR ON CHAN 9 AFTER SKIP TO 1	
3 or 43	DID NOT BR ON CHAN 12 AFTER SKIP TO 1	
25 or 65	(blanks)	
26 or 66	BRANCHED ON CHAN 9 AFTER SKIP TO 9	
34 or 74	(blanks)	
35 or 75	BRANCHED ON CHAN 12 AFTER SKIP TO 12	
36 or 76	END OF TEST	

ONE EXAMPLE OF ERROR PRINT-OUT:

BRANCH CHANNEL 9 & 12    2020B

	(blanks)	
1 or 41		
2 or 42	BRANCHED ON CHAN 9 AFTER SKIP TO 1	ERROR
Stop 3 or 43	BRANCHED ON CHAN 12 AFTER SKIP TO 1	ERROR
Stop 4 or 44		
25 or 65	(blanks)	
26 or 66	DID NOT BR ON CHAN 9 AFTER SKIP TO 9	ERROR
Stop 27 or 67		
34 or 74	(blanks)	
35 or 75	DID NOT BR ON CHAN 12 AFTER SKIP TO 12	ERROR
Stop 36 or 76	END OF TEST	

↑  
Sense Switch E ON