Procedure for Running Branch Channel 9 and 12 Test from Tape

1. Manually enter "1" in Location S61.
2. Set Sense Switch "F" to the OFF position.
   NOTE: This will allow the Branch Channel 9 and 12 Test to be executed with all other tests that may be chained.

Procedure for Running ONLY Branch Channel 9 and 12 Test from Tape

1. Manually enter Block No. 2020 in Locations S73-S76, and "1" in Location S61.
2. Set Sense Switch "F" to the ON position.
   NOTE: This will allow only the Branch Channel 9 and 12 Test to be executed, by-passing all the others.

Checking Procedure

Two print-out examples are shown below which can be used to visually check the results.

EXAMPLE OF CORRECT PRINT-OUT:

BRANCH CHANNEL 9 & 12 2020B

(Spacing may vary from 2 to 40 spaces depending upon the position of the carriage tape when the title is printed)

Line No. on Tape	
1 or 41	(blanks)
2 or 42	DID NOT BR ON CHAN 9 AFTER SKIP TO 1
3 or 43	DID NOT BR ON CHAN 12 AFTER SKIP TO 1
25 or 65	(blanks)
26 or 66	BRANCHED ON CHAN 9 AFTER SKIP TO 9
34 or 74	(blanks)
35 or 75	BRANCHED ON CHAN 12 AFTER SKIP TO 12
36 or 76	END OF TEST

ONE EXAMPLE OF ERROR PRINT-OUT:

BRANCH CHANNEL 9 & 12 2020B

	1 or 41	(blanks)	
	2 or 42	BRANCHED ON CHAN 9 AFTER SKIP TO 1	ERROR
Stop	3 or 43	BRANCHED ON CHAN 12 AFTER SKIP TO 1	ERROR
Stop	4 or 44		
	25 or 65	(blanks)	
	26 or 66	DID NOT BR ON CHAN 9 AFTER SKIP TO 9	ERROR
Stop	27 or 67		
	34 or 74	(blanks)	
	35 or 75	DID NOT BR ON CHAN 12 AFTER SKIP TO 12	ERROR
Stop	36 or 76	END OF TEST	

Sense Switch E ON