

CUSTOMER ENGINEERING TESTS
FOR THE 1401 DATA PROCESSING SYSTEM

Sheet 1 of 5
E.C. 110378B
Part No.451479
Block No.3700A

MODIFY ADDRESS

Purpose of Test

To test the Modify Address circuitry by adding two 3-character fields and comparing the result with the Result Should Be Field. For unequal conditions the machine either stops to permit console checking or prints the results depending upon the setting of Sense Switch E.

Units Required

1401 Processing Unit
1402 Card Reader or 729 Tape Drive
1403 Printer (optional)
1406 Storage Unit

<u>Operations Used</u>	<u>Code</u>
Clear	(/)
Set Word Marks	(,)
Load	(L)
Modify Address	(#)
Clear Word Marks	(x)
Compare	(C)
Branch	(B)
Print	(2)
Stop (error)	(.)

Method of Test

The complete test block consists of the following cards:

1. Title Card (0A)
2. Two Program Chaining Routine Cards (02-03)
3. Three Title and Headings Print Routine Cards (04-06)
4. Four special program cards to set up instructions that are effective only when tests are run from tape (07-10)
5. Program Instruction Cards (11-44)
6. Detail Cards (45-58)

Four Sense Switches may be brought into play as follows:

Sense Switch B ON - permits scoping of the Modify Address operation
as often as desired.

Sense Switch C OFF - no printing for correct results.
ON - prints for correct results.

Sense Switch D ON - repeats the program for an individual card as often
as desired.

Sense Switch E OFF - prints for error results.
ON - stops for error results.